

The length of the standard cable (1,000 mm) may be adjusted to the current project. Attention: In case of a modular structure, a new electrical supply wire must be added every 25mts of linear section and/or when the total power of the whole linear section is above 1100W.

Tc max=85°C Risk group(EN 62471:2008)=1

Installation cable must support 110°C temperature. Feeding cable must be cable pipe 3x1 mm<sup>2</sup> and 3x1,5 mm<sup>2</sup>. Installation may require advice.

Do not accumulate excess of cable into the fixture.

Attention: We do recommend being installed by two people for proper safety.


6.75Kg

General safety instructions: information on restrictions related to use of the light fixtures (class, IP, etc), can be found both on the fixture label and on our website at [www.rovasi.com](http://www.rovasi.com).

The wiring schematics can be found on page 2 of the document.







### ELECTRONIC EQUIPMENT:

- S:** On/Off.
- A:** 1-10V (only downlight position).
- D:** DALI/DSI/switchDIM (only downlight position).
- SE:** On/Off + Emergency Kit .
- AE:** 1-10V+Emergency Kit .
- DE:** DALI/DSI/switchDIM +E-Kit .
- DDE:** DALI/DSI/switchDIM +E-Kit (DALI). There are available accessories for dimming devices.



17.76W / 150mA

- 536KTA.1-I807
- 536KTA.1-I808
- 536KTA.1-I809
- 536KTA.1-I810
- 536KTA.1-I812
- 536KTA.1-I813



This product contains a light source of energy efficiency class D + C.

LED technology and performance data are constantly changing. Current details should therefore be checked with ROVASI in order to ensure that its still the mostup to date reference. Updated data will be supplied on request. [15.12.2022]



BSI Cert ISO 9001:2015 - n°FM 39346  
BSI Cert ISO 14001:2015 - n°EMS 554685

Ronda de la Font-Grossa 15  
Pol. Ind. La Gavarra  
08540 Centelles | Barcelona  
Spain

T. 34 93 881 35 12  
T. 34 93 881 37 13


info@rovasi.com  
**rovasi.com**

# WIRING GUIDELINES

## Installation instructions. Mains supply wires

- Wiring type and cross section
- Solid wire with a cross section of 0.5 – 1.5 mm<sup>2</sup>.
- Strip 8-9mm of insulation from the cables to ensure perfect operation of the push terminals.
- Use one wire for each terminal connector only.
- Use each strain relief channel for one cable only.
- Installation may require advice from a qualified person.
- Single lights apt for indoor use (not outdoor).

## Wire preparation:




## Wiring guidelines

- All connections must be kept as short as possible to ensure good EMI behaviour.
- Earthing is not required for the device to operate but will improve the EMI behaviour.
- The max. secondary cable length is 2m (4m circuit).
- Secondary switching is not permitted.
- Incorrect wiring can damage LED modules.




Loose wire through twisting and pulling or using a Ø1mm release tool.


Circuit diagram S: Standard ON/OFF




Circuit diagram D: DALI/DSI/SwitchDIM/corridorFUNCTION




Circuit diagram A: 1-10V [to consult]




Circuit diagram DB: DALI



# UPGRADEABLE, REPLACEABLE, REPAIRABLE




The light source in this luminaire should only be undertaken by the manufacturer or his service agent or a similar qualified person.




The servicing of the driver in this luminaire should only be undertaken by the manufacturer or his service agent or a similar qualified person.

1



2



3

