
TIRET 300







351TRT.1-I1467







Surface mounted linear downlights with symmetrical light distribution to achieve an effective task or general lighting.

Linear fixture in 566mm length and in a width of 40mm.

Powder painted extruded aluminium profile available in assorted finishes, customized RAL under request. Opal extruded polycarbonate diffuser.

Highly efficient linear printed circuit board.

650°

Accessories available to create customized linear systems.

Built-in driver, included.

Electronic options for lighting control: DALI-2.

The driver contained in this luminaire complies with European Directive 2009/125/EC establishing flicker

limits: PstLM \leq 1 and SVM \leq 0.4. Passive temperature management.

Ceiling-mounted using cleats.

It is possible to combine different lengths and junction modules in different ways to create customized systems.

lmax=534 Cd

100

300

η=100.0% ▼ M ▼ Ø ▼LUX

1 2.0

2 4.1 134

3 6.1

4

5 10.2 21 91°

534

33 8.2

Luminaire luminous flux: 1071lm Luminaire connected power: 12,02 W Luminaire efficiency: 89 lm/W Light source luminous flux: 1700lm Light source power: 10,82 W Constant Current: 250 mA

CRI: >90 R9 57

Colour Temperature: 2700K

Chromaticity Tolerance: MacAdam 3

Beam Angle: 91° **LOR:** 63%

LED reliability at nominal Ta = 25°C: 100.000h L80B10

Photobiological safety group: 0

This product contains a light source of energy efficiency class C

Electronic Equipment

S: On/Off (AC/DC, NOT looping through capable)

D: DALI-2/switchDIM/corridorFUNCTION

B: Bluetooth-Casambi

1: RAL9010: Pure White, 2: RAL9005: Jet Black, 4: RAL7016: Anthracite Grey, 7: RAL9006: White Aluminium

Upgradeable, Replaceable, Repairable





Note

LED technology and performance data are constantly changing. Current details should therefore be checked with ROVASI in order to ensure that it is still the most up to date reference. Updated data will be supplied on request. [Last revised on 27.07.2025]

5 years guarantee



Contact

T. +34 93 881 37 13 www.rovasi.com

^{*}Add the suffix **-S, -D, -B** after the reference to indicate your electronic equipment choice.