GOWEL 800



η=100.0% ▼ M ▼ Ø ▼LUX

2

3 0.91 1060

4 1.21 596

0.30 9538

0.60 2385

1.51

17°





800GWL.1-I1703



Linear projectors with symmetrical light distribution to achieve an effective task or general lighting.

Linear fixture in 295mm length and in a width of 70mm.

Powder painted extruded aluminium profile available in assorted finishes, customized RAL under request.

Range of PMMA optics to achieve specific photometric results.

Highly efficient linear printed circuit board.

Built-in driver, included.

Electronic options for lighting control: DALI-2.

The driver contained in this luminaire complies with European Directive 2009/125/EC establishing flicker

limits: PstLM \leq 1 and SVM \leq 0.4. Passive temperature management.

Ceiling or wall mounted using adjustable supports.

Matching products:

GOWEL 100 recessed with frame. GOWEL 200 frameless recessed. GOWEL 300 surface mounted.

GOWEL 400 pendant.

Luminaire luminous flux: 1502lm Luminaire connected power: 12,1 W Luminaire efficiency: 124 lm/W Light source luminous flux: 1650lm

Light source power: 9,1 W Constant Current: 300 mA

CRI: 80

Colour Temperature: 3000K

Chromaticity Tolerance: MacAdam 3

Beam Angle: 17° **LOR:** 91%

LED reliability at nominal Ta = 25°C: 72.000h L80B10

Photobiological safety group: 1

This product contains a light source of energy efficiency class C

Electronic Equipment

S: On/Off
D: DALI-2/switchDIM

Finishes

1: RAL9010: Pure White, 2: RAL9005: Jet Black, 4: RAL7016: Anthracite Grey, 7: RAL9006: White Aluminium

Upgradeable, Replaceable, Repairable





Note

LED technology and performance data are constantly changing. Current details should therefore be checked with ROVASI in order to ensure that it is still the most up to date reference. Updated data will be supplied on request. [Last revised on 26.07.2025]

5 years guarantee



BSI Cert ISO 9001:2015 - nºFM 39346 BSI Cert ISO 14001:2015 - nºEMS 554685

ROVASIS.L.

Contact

T. +34 93 881 35 12

info@rovasi.com www.rovasi.com

T. +34 93 881 37 13

B: Bluetooth-Casambi

^{*}Add the suffix -S, -D, -B after the reference to indicate your electronic equipment choice.