
KAUTTA 800







835KTA.1-I1514



Linear projectors with symmetrical light distribution to achieve an effective accent, task or general

Linear fixture in 1128mm length and in a width of 44mm.

Powder painted extruded aluminium profile available in assorted finishes, customized RAL under request.

PMMA optics for controlling and directing the light.

Highly efficient linear printed circuit board.

Built-in driver, included.

Electronic options for lighting control: DALI-2.

The driver contained in this luminaire complies with European Directive 2009/125/EC establishing flicker

Imax=1773 Cd

η=93.4% ▼ M ▼ Ø ▼ LUX

0.79 1772

197

1.58

1

3 2.4

4 3.2 111 43°

limits: PstLM \leq 1 and SVM \leq 0.4. Passive temperature management.

Ceiling or wall installation with adjustable fixing brackets.

Other options available:


Recessed.

Frameless recessed.

Surface-mounted.

Pendant.

Wall-mounted.



CRI: >80

Colour Temperature: 4000K

Chromaticity Tolerance: MacAdam 3

Beam Angle: 43° **LOR:** 93%

LED reliability at nominal Ta = 25°C: 100.000h L80B10

Photobiological safety group: 0

Cd/Klm: 704

This product contains a light source of energy efficiency class B

Electronic Equipment

S: On/Off (AC/DC, NOT looping through capable)
SE: On/Off (AC/DC) + Battery 3h
D: DALI-2/switchDIM/corridorFUNCTION
DE: DALI-2/switchDIM+ 3 hours battery DDE: DALI-2/switchDIM+ 3 hours battery (DALI)

B: Bluetooth-Casambi

1: RAL9010: Pure White, 2: RAL9005: Jet Black, 4: RAL7016: Anthracite Grey, 7: RAL9006: White Aluminium

Upgradeable, Replaceable, Repairable





Note

LED technology and performance data are constantly changing. Current details should therefore be checked with ROVASI in order to ensure that it is still the most up to date reference. Updated data will be supplied on request. [Last revised on 27.07.2025]

5 years guarantee



BSI Cert ISO 9001:2015 - nºFM 39346 BSI Cert ISO 14001:2015 - nºEMS 554685

ROVASIS.L.

T. +34 93 881 35 12

info@rovasi.com www.rovasi.com

T. +34 93 881 37 13

^{*}Add the suffix -S, -SE, -D, -DE, -DDE, -B after the reference to indicate your electronic equipment choice.