TEKNO SQ Minidownlights



η=100.0% ▼ M ▼ Ø ▼LUX

1

2

3 1.49

4 1.98 90


5 2.5


0.50 1441

58

0.99 360 289







102TSS.1-R711
















Imax=1441 Cd



Square design in 60mm x 60mm.

Body powder painted in various finishes, customized RAL under request.

Accessory available to increase the protection rating to IP44 from underneath [reference M2.A0035].

Honeycomb anti-dazzle screen accessory to increase visual comfort [reference M6.A0035].

Remote driver included.

Electronic options for lighting control: DALI-2.

3 hours battery available as option*.

Passive temperature management: heat dissipation via aluminium heat sink.

Ceiling-mounted using galvanised steel support with spring clamps.

Luminaire luminous flux: 495lm Luminaire connected power: 4.7 W Luminaire efficiency: 105 lm/W Light source luminous flux: 707lm

Light source power: 101-102-103TSS_4.7W_en W

Constant Current: 150 mA

CRI: >90

Colour Temperature: 4000K

Chromaticity Tolerance: MacAdam 3

Beam Angle: 28°

LOR: 70%

Average Service Life: 50000h LED reliability: >53000h L80B50

UGR: >21 under the below indicated parameters

Room dimensions X=4H/8H Reflectance 20% | 50% | 70% Luminaire spacing = 1m

Photobiological safety group: 1

Cd/Klm: 2910 Imax: 1441 Cd

This product contains a light source of energy efficiency class A++

Electronic Equipment

D: DALI-2/switchDIM/corridorFUNCTION **DE:** DALI-2/switchDIM+ 3 hours battery **DDE:** DALI-2/switchDIM+ 3 hours battery (DALI)

2: RAL9005: Jet Black, 4: RAL7016: Anthracite Grey, 7: RAL9006: White Aluminium, 1: RAL9010: Pure White

Upgradeable, Replaceable, Repairable





Note

LED technology and performance data are constantly changing. Current details should therefore be checked with ROVASI in order to ensure that it is still the most up to date reference. Updated data will be supplied on request. [Last revised on 03.05.2024]

5 years guarantee



BSI Cert ISO 9001:2015 - nºFM 39346 BSI Cert ISO 14001:2015 - nºEMS 554685 T. +34 93 881 35 12

info@rovasi.com www.rovasi.com

T. +34 93 881 37 13

^{*}Add the suffix -D, -DE, -DDE after the reference to indicate your electronic equipment choice.