

CONICAL

Small recessed downlights









101CNC.1-R524



IP20













Imax=1939 Cd





η=100.0% ▼ M ▼ Ø ▼LUX

1

2 0.75 485

3 1.12

4 1.49 121

5 1.87

0.37 1939

78

21°

Recessed ceiling-mounted small downlight with symmetrical light distribution to achieve an effective task or general lighting.

Circular design in diameter 85mm.

Powder painted aluminium conical trim available in assorted finishes, customized RAL under request. Accessory available to increase the protection rating to IP44 from underneath [reference M2.H0085].

Honeycomb anti-dazzle screen accessory to increase visual comfort [reference M6.A0050].

Remote driver included.

Electronic options for lighting control: DALI-2.

3 hours battery available as option.

Passive temperature management: heat dissipation flows through an aluminium heat sink diffuser.

Ceiling-mounted by spring clamps for easy installation, ceiling thickness up to 25mm.

Luminaire luminous flux: 487lm Luminaire connected power: 5.66 W Luminaire efficiency: 86 lm/W Light source luminous flux: 560lm Light source power: 5 W Constant Current: 150 mA

CRI: >90

Colour Temperature: 4000K

Chromaticity Tolerance: MacAdam 3

Beam Angle: 21° **LOR:** 87%

Average Service Life: 50000h LED reliability: >50000h L70B50

UGR: <16

Photobiological safety group: 1

This product contains a light source of energy efficiency class F

Electronic Equipment

K: On/Off (basic)
S: On/Off (AC/DC)

SE: On/Off (AC/DC) + Battery 3h
D: DALI-2/switchDIM/corridorFUNCTION
DE: DALI-2/switchDIM + 3h battery

B: Bluetooth-Casambi

Finishes

2: RAL9005: Jet Black, 4: RAL7016: Anthracite Grey, 7: RAL9006: White Aluminium, 1: RAL9010: Pure White

Upgradeable, Replaceable, Repairable





Note

LED technology and performance data are constantly changing. Current details should therefore be checked with ROVASI in order to ensure that it is still the most up to date reference. Updated data will be supplied on request. [Last revised on 05.05.2024]

5 years guarantee



Spain

T. +34 93 881 37 13

^{*}Add the suffix -K, -S, -SE, -D, -DE, -B after the reference to indicate your electronic equipment choice.