CONICAL

Small recessed downlights



η=100.0% ▼ M ▼ Ø ▼LUX

1

2

3 1.12


4 1.49 182


0.37 2907

0.75 727

1.87 116 21°







101CNC.1-R640



IP20 850°











Imax=2907 Cd



Recessed ceiling-mounted small downlight with symmetrical light distribution to achieve an effective task or general lighting.

Circular design in diameter 85mm.

Powder painted aluminium conical trim available in assorted finishes, customized RAL under request. Accessory available to increase the protection rating to IP44 from underneath [reference M2.H0085].

Honeycomb anti-dazzle screen accessory to increase visual comfort [reference M6.A0050].

Remote driver included.

Electronic options for lighting control: DALI-2.

3 hours battery available as option.

Passive temperature management: heat dissipation flows through an aluminium heat sink diffuser.

Ceiling-mounted by spring clamps for easy installation, ceiling thickness up to 25mm.

Luminaire luminous flux: 730lm Luminaire connected power: 9.77 W Luminaire efficiency: 75 lm/W Light source luminous flux: 840lm Light source power: 8.8 W Constant Current: 250 mA

CRI: >90

Colour Temperature: 3000K

Chromaticity Tolerance: MacAdam 3

Beam Angle: 21° **LOR:** 87%

Average Service Life: 50000h LED reliability: >50000h L70B50

UGR: <19

Photobiological safety group: 1

This product contains a light source of energy efficiency class F

Electronic Equipment

K: On/Off (basic)
S: On/Off (AC/DC)

SE: On/Off (AC/DC) + Battery 3h
D: DALI-2/switchDIM/corridorFUNCTION
DE: DALI-2/switchDIM + 3h battery

B: Bluetooth-Casambi

Finishes

2: RAL9005: Jet Black, 4: RAL7016: Anthracite Grey, 7: RAL9006: White Aluminium, 1: RAL9010: Pure White

Upgradeable, Replaceable, Repairable





Note

LED technology and performance data are constantly changing. Current details should therefore be checked with ROVASI in order to ensure that it is still the most up to date reference. Updated data will be supplied on request. [Last revised on 05.05.2024]

5 years guarantee



Spain

^{*}Add the suffix -K, -S, -SE, -D, -DE, -B after the reference to indicate your electronic equipment choice.