# Minidownlights



▼Ø ▼LUX

0.43 4126

0.85 1032

2.1 165


1


2

3 1.28 458

4 1.70 258







## 106TKN.1-R649

















Recessed ceiling-mounted small downlights with symmetrical light distribution to achieve an effective task, accent or ambient lighting.

Circular design in diameter 70mm.

Powder painted die-cast aluminium trim available in assorted finishes, customized RAL under request. Accessory available to increase the protection rating to IP44 from underneath [reference M2.A0070]. Honeycomb anti-dazzle screen accessory to increase visual comfort [reference M6.A0050].

Remote driver included.

Electronic options for lighting control: DALI-2.

Passive temperature management: heat dissipation flows through an aluminium heat sink. Ceiling-mounted by spring clamps for easy installation, ceiling thickness up to 25mm.

Light source power: 10 W Luminaire connected power: 11.27 W Constant Current: 300 mA Light source luminous flux: 940lm Luminaire luminous flux: 940lm **CRI:** >90

Colour Temperature: 3000K

Chromaticity Tolerance: MacAdam 3

Beam Angle: 24° **LOR:** 100%

Average Service Life: 50000h LED reliability: >50000h L90B10

**UGR:** <16

Photobiological safety group: 1

**Cd/Klm:** 4408

Luminaire efficiency: 83 lm/W

Imax: 4143 Cd

This product contains a light source of energy efficiency class F

### **Electronic Equipment**

K: On/Off (basic) S: On/Off (AC/DC)

SE: On/Off (AC/DC) + Battery 3h
D: DALI-2/switchDIM/corridorFUNCTION

DE: DALI-2/switchDIM + 3h battery

B: Bluetooth-Casambi

2: RAL9005: Jet Black, 4: RAL7016: Anthracite Grey, 7: RAL9006: White Aluminium, 1: RAL9010: Pure White

#### Upgradeable, Replaceable, Repairable





Note

LED technology and performance data are constantly changing. Current details should therefore be checked with ROVASI in order to ensure that it is still the most up to date reference. Updated data will be supplied on request. [Last revised on 25.04.2024]

5 years guarantee



Spain

<sup>\*</sup>Add the suffix -K, -S, -SE, -D, -DE, -B after the reference to indicate your electronic equipment choice.