

advice.



Do not accumulate excess of cable into the fixture.



Tc max=85°C  
Risk group (EN 62471:2008)=1  
Installation cable must support  
110°C temperature. Feeding cable  
must be cable pipe 3x1 mm<sup>2</sup> and  
3x1,5 mm<sup>2</sup>. Installation may require

Attention: We do recommend  
being installed by two people for  
proper safety.




General safety instructions: information on restrictions related  
to use of the light fixtures (class, IP, etc), can be found both on  
the fixture label and on our website at [www.rovasi.com](http://www.rovasi.com).

The wiring schematics can be found on page 2 of the  
document.

### ELECTRONIC EQUIPMENT:

**S:** On/Off .

**D:** DALI/DSI/switchDIM. There are accessories available for  
dimming devices.








16W / 350mA

151RNA.1-I737  
151RNA.1-I738  
151RNA.1-I739  
151RNA.1-I740  
151RNA.1-I742  
151RNA.1-I743

### ACCESSORIES

+MODULAR	L mm	M5.Q0068	M5.E0068
	585		
	865		
	1145		
	1425		
	2825		




LED technology and performance data are constantly changing. Current details should therefore be checked with ROVASI in order to ensure that its still the mostup to date reference. Updated data will be supplied on request. [05.09.2022]

## Installation instructions. Mains supply wires

- Wiring type and cross section
- Solid wire with a cross section of 0.5 – 1.5 mm<sup>2</sup>.
- Strip 8-9mm of insulation from the cables to ensure perfect operation of the push terminals.
- Use one wire for each terminal connector only.
- Use each strain relief channel for one cable only.
- Installation may require advice from a qualified person.
- Single lights apt for outer use.

## Wire preparation:




## Wiring guidelines

- All connections must be kept as short as possible to ensure good EMI behaviour.
- Earthing is not required for the device to operate but will improve the EMI behaviour.
- The max. secondary cable length is 2m (4m circuit).
- Secondary switching is not permitted.
- Incorrect wiring can damage LED modules.


Loose wire through twisting and pulling or using a Ø1mm release tool.




## Circuit diagram S: Standard ON/OFF




## Circuit diagram D: DALI/DSI/SwitchDIM/corridorFUNCTION



## Circuit diagram A: 1-10V [to consult]



## Circuit diagram DB: DALI



## Maximum lead length

LED 3m<sup>®</sup>  
Status indication LED 1m  
Batteries 1.3m  
Insolation and electric strength testing of luminaires

• Note: The length of LED module must not be exceeded.  
Note that the length of the EM converterLED leads to the LED module will be added to the length of the leads from the control gear to the EM converterLED module when considering the lead length of the control gear.  
Leads should always be kept as short as possible.


## Wiring guidelines

- The LED terminals, battery, indicator LED and test switch terminals are classified as SELV (output voltage <60V DC).
- Keep the wiring of the input terminals separated from the wiring of the SELV equivalent terminals or consider special wiring (double insulation, 6mm creepage and clearance) when these connections should be kept SELV.
- The output to the LED is DC but has high frequency content, which should be considered for good EMC compliance.
- LED leads should be separated from the mains connections and wiring for good EMC performance.
- Maximum lead length on the LED terminals in 3m. For a good EMC performance keep the LED wiring as short as possible.
- Maximum lead length for the Test switch and indicator LED connection is 1m.
- The test switch and indicator LED wiring should be separated from the LED leads to prevent noise coupling.
- Battery leads are specified with 0.5mm cross section and a length of 1.3m.

EM: Electromagnetic  
EMC: Electromagnetic Compatibility  
DC: Direct current  
SELV: Safety extra low voltage


## Circuit diagram SE: Emergency kit

EM converter LED BASIC with a standard LED control gear and one LED module for mains and emergency operation.




## Circuit diagram DE: DALI/DSI/SwitchDIM/corridorFUNCTION + E-kit

EM converter LED BASIC with a DALI LED control gear and one LED module for mains and emergency operation.



## Circuit diagram DBE: DALI + Emergency Kit

EM converter LED BASIC with a DALI BASIC LED control gear and one LED module for mains and emergency operation.



## Circuit diagram DDE: DALI/DSI/SwitchDIM/corridorFUNCTION + E-kit (DALI)

EM converter LED PRO with a DALI LED control gear and one LED module for mains and emergency operation.

