

4 ↑ x4

3 ↑

2 ↓

1 ↓

M4x16 x4

M4x16 x3

305
256
305
90
Ø315
tc

Tc max=85°C Risk group(EN 62471:2008)=1

110 °C

Installation cable must support 110°C temperature. Feeding cable must be cable pipe 3x1 mm². Installation may require advice.

Not suitable for covering with thermally insulating material.

Do not accumulate excess of cable into the fixture.

359mm

General safety instructions: information on restrictions related to use of the light fixtures (class, IP, etc), can be found both on the fixture label and on our website at www.rovasi.com.

The wiring schematics can be found on page 2 of the document.

ELECTRONIC EQUIPMENT:





S: On/Off.
D: DALI/DSI/switchDIM.
A: 1-10V. There are accessories available for dimming devices.

1,5 ——— 356 ——— } 90

18.14W / 600mA

108CND.1.02-I637
108CND.1.02-I638

Mounting screws not included.



This product contains a light source of energy efficiency class C.

LED technology and performance data are constantly changing. Current details should therefore be checked with ROVASI in order to ensure that its still the mostup to date reference. Updated data will be supplied on request. [13.12.2022]

WIRING GUIDELINES


Installation instructions. Mains supply wires

- Wiring type and cross section
- Solid wire a cross section of 0.2 - 1.5mm². Strip 8,5-9,5 mm of insulation from the cables to ensure perfect operation of terminals.
- Use one wire for each terminal connector only.
- Use each strain relief channel for one cable only.
- Installation may require advice from a qualified person.
- Single lights apt for inner use (no outer)


Wiring guidelines

- The cables should be run separately from the mains connections and mains cables to ensure good EMC conditions.
- The max. secondary cable length is 2m (4m circuit). Secondary switching is not permitted.
- Incorrect wiring can damage LED modules.
- The LED Driver has no inverse-polarity protection on the secondary side. Wrong polarity can damage led modules with no inverse-polarity protection.


Release of the wiring




Circuit diagram S:Electronic constant current drivers




Circuit diagram D:DALI/DSI/SwitchDIM/corridorFUNCTION



UPGRADEABLE, REPLACEABLE, REPAIRABLE




The light source contained in this luminaire shall only be replaced by the manufacturer or his service agent or a similar qualified person.




The driver contained in this luminaire shall only be replaced by the manufacturer or his service agent or a similar qualified person.


1



2



3



4

